



The Smartvest Wireless Socket enables you to switch on a number of your electronic devices, with the option to do this either yourself via the free and convenient app or automatically via a personalised time schedule. In other words, it gives you the option of different smart functions, such as presence simulation or setting the coffee machine to switch on before you have got out of bed. There are almost no limits on what you can do with the Socket and app, which gives everyday life the level of "smartness" and security it should have.

Technologies

- Smartvest extension for switching connected devices
- Smart light control: system armed/disarmed, motion detected, light on
- Visual notification via blue LED when starting up and functioning
- Repeater function to extend the range of a Smartvest component (e.g. detector)
- Manual switching on socket possible
- Option to control the socket via the Smartvest app

Technical data - 4003318388330

AC voltage supply	250 V
Area of application	Inside
Certifications	GS
Colour	White
Compatible with Secvest	No
Compatible with Smartvest	Yes
Dimensions	(B x L x H) 55 x 31 x 99 mm
Display	LED
Gross weight	0,176 kg
Housing material	Plastic

4003318388330



Security Tech Germany

Art.-Nr. FUHA35000A

Seite 2 von 2

Technical data - 4003318388330

Luminous colour	Blue / Orange
Max. humidity	80 %
Max. operating temperature	35 °C
Min. operating temperature	0 °C
Net weight	0,129 kg
Plug type	Schuko plug on device (type:F) / Schuko socket on device (type:F)
Radio frequency	868 MHz
Radio modulation	FSK
Standby power consumption	10 mA
Switching power	< 3680 W
Tamper protection	No
Transmission power	4,5 dBm
Wireless range	(Depending on installation) 30 - 100 m