ABUS Z-Wave button



Art.-Nr. SHBE10000

Seite 1 von 2



Lights, shutters, heating and more: now all you need to switch on your smart home components is a wireless, battery-operated button.

Among other things, this enables you to get your day off to a relaxed start: with the ABUS Z-Wave Button on your bedside table, you can switch on the heating in the bathroom (press briefly), the light (press and hold down) and open the shutters (press twice).

The flexible Z-Wave Button is ideal for locations and places, where you normally don't have your smartphone or your Z-Wave Remote Control to hand.

Whether it's fixed in place with double-sided adhesive tape, screwed on or placed on the living room table, the convenient button can execute up to six different commands.

You can set your own preferred configuration in just a few steps: simply launch the Z-Wave app and program the button into your Z-Wave Gateway or your Smart Friends Box. The button's two conventional AAA batteries last for up to two years without being changed.

ABUS Z-Wave button



Art.-Nr. SHBE10000

Seite 2 von 2

Technologies

- Scenes programmed in the Z-Wave Gateway can be safely and quickly switched on and off at the touch of a button without having to open the app
- The rocker button has 2 buttons (top and bottom), for each button a distinction is made between short press, double press and long press
- This means that up to 3 different scenes can be switched on and off as the button can send a total of 6 different commands to the Z-Wave Gateway
- With just one button, an entire room can be controlled. For example: heating up/down, lighting on /off and shutter up/down
- The button can either be glued to the wall or screwed. Alternatively, it can also be used on the move, for example on the bedside table or living room table
- The wireless button can be operated with 2 standard AAA batteries for up to 2 years without battery replacement

Area of application	Inside
Battery - battery operation	Yes
Battery - max. battery life	2 y
Battery - quantity	2
Battery - type	AAA
Colour	White
Dimensions	80x15x80 mm
Display	LED
Housing material	Plastic
Radio frequency	868,42 MHz
Radio modulation	Z-Wave Plus (S2) / FSK (BFSK / GFSK)
Transmission power	<5 dBm
Wireless range	(Depending on installation) 20 - 100 m

Technical data - ABUS Z-Wave button